
MANUAL CALL POINT W/ SELFVERIFY - BF-502/EX

Interactive fire detection systems Product Datasheet

Technical specifications and instructions

Features

- Break glass unit for use in harsh environmental
- conditions
- Weather proof
- Corrosion resistant GRP
- Protection degree IP66
- Short circuit isolator in each unit
- Automatic addressing
- Proven technology
- With SelfVerify function for reduced maintenance/testing and increased reliability
- Designed to meet the requirement of the major maritime classification societies



BF-502/EX is a manual call point for use in hazardous area zone 0, 1 or 2. It must be connected to the approved barrier BZ-500. The call point has been designed for use with Autronica's interactive fire detection systems, and comprises the SelfVerify function. This function ensures the highest grade of reliability and the lowest degree of manual testing, because all units comprising this function are automatically self-tested once every 24 hours.

The high IP degree and mechanical strength of the enclosure makes the call point suitable for outdoor applications in industrial, maritime and offshore installations.

The call point must be installed according to local regulations, which normally means along escape routes, landings and exits.


Principle

Break glass operation, releasing alarm switch. Reset when a new glass is mounted.

SelfVerify: the call point's ability to initiate alarms is regularly checked.

Schedule Drawing

No modifications permitted without reference to the Notified Body



Versions

• BF-502* Manual call point with SelfVerify

BF-502/EX Manual call point with SelfVerify.
 Ex ia version for use in zone 0, 1 and 2

BF-502/N* Manual call point with SelfVerify.
 Ex ic version for use in zone 2 only

* See separate data sheet




Technical specifications		
Weight	0,5 kg	
Material	Glass reinforced polyester	
Colour	Red	
Voltage	10 - 27 VDC	
Current consumption stand by:	0,3 mA	
Environm. requirement	EN 54	
Degree of protection	IP66*	
Working temperature	-25 - + 70 °C	
Storage temperature	-55 - + 70 °C	
Cable inlets	2 x M20	
Maintenance	Replace broken glass	
Service	Replace if faulty	
Certificates	See website	
Notified body	Nemko ID No. 0470	
,	CSA	
Type examination certificate	NEMKO 03ATEX218X	
	IECEX NEM 11.0009X	
Directives and standards	2014/34/EU (ATEX) EN 60079-0:2012	
	EN 60079-0:2012 EN 60079-11:2012	
	IEC 60079-0:2011	
	IEC 60079-11:2011	
	2014/30/EU (EMC)	
	Immunity: EN 50130-4:2011 Emission: EN 61000-6-3:2001	
	LIIIISSIOII. LIN 01000-0-3.2001	
	CAN/CSA-C22.2 No. 0-10	
	CAN/CSA-C22.2 No. 205-12	
	CAN/CSA-60079-0-11	
	CAN/CSA-60079-1-11 CAN/CSA-60079-11-11	
	CAN/CSA-C22.2 No. 60529-05	
	UL 464, 9th Edition	
	UL 60079-0, 5th Edition UL 60079-1, 6th Edition	
	UL 60079-11, 5th Edition	
	ANSI/IEC C0E20-2004	
	ANSI/IEC 60529:2004 ANSI/ISA-60079-26: 2011	
Ex parameters	II 1G Ex ia IIC T5 Ga	
	Class 1, Zone 0, AEx ia IIC T5 Ga	
	Ui = 15,75V	
	li = 63,5mA	
	Ci = 21,6nF	
	Li = 0	
	Pi = 0,44W	
	Warning: Do not rub.	
<u> </u>	<u> </u>	

^{*}requires approved cable glands and/or plugs of minimum the same IP level.

Autronica Fire and Security AS Tel.: +47 90 90 55 00 E-mail: info@autronicafire.no www.autronicafire.com Page 2

Product Name	Part number	Description	
BF-502/EX	116-BF-502/EX	Manual call point with 2 glands (type 116-6571-011.1920)	
Accessories			
	116-6571-011.1920	GLAND ST M20X1,5 PG13,5 (1 pcs)	
	116-4890-021.0001	Lift flap PC	
	116-4890-021.0010	Lift flap SS	

Connections



Dimensions

